

MIXX 12

DIGITAL MIXER WITH DANTE
INTERFACE

MIXX 12 DIGITAL MIXER



Dante™
SPOKEN HERE

MIXX12 Digital Mixer is a 12 inputs and 6 outputs digital wireless control mixer, is a new mixer through the tablet computer application control, can support all iOS, Windows 8 tablet and Android tablet. Using Wi-Fi to connect, anywhere in the wireless network within the scope of control. With 12 inputs/12 channels of broadcast quality microphone amplifier, 6 outputs (two main and 4 aux outs). Adopt high performance 40 bit floating-point digital signal processor, 24 bit AD/DA converter. Built-in effects processor, compression and limiter, gate plug-ins, parametric equalizer. Wireless control mode makes you can walk between the stage and the crowd. It is 12-channel digital mixer that with the iPad and tablet computer touch. Equip with DANTE card.

Product Specification



MIXX 12
Digital Mixer

Sample Rate	24bit, 48kHz
Frequency Respond:	20 Hz to 20 kHz +0/-1 dB
Latency	1.5 ms
T.H.D.	<0.005%
Noise-Mic input to main output	-72dBv Single channel-Max fader(A weighted) -90dBv Single channel-Min fader(A weighted)
Input crosstalk (adjacent channel)	<-120 dB @ 1 kHz
S/N	93dB One channel and main fader at unity(A-weighted)
Dynamic Range	110dB One channel and main fader at unity(A-weighted)
CMRR	>70 dB @ 1 kHz
Input Impedance	3.3kΩ(XLR Balance) 30 kΩ(1/4")
Gain	0 to 60 dB (XLR)
Output Impedance	600Ω(XLR Balance)
Max Output Level	+21 dBu(XLR Balance)
Power Supply	DC 12V-15V (3.5A)
Dimension(mm)	448(L) × 132(H) × 191(D)
Weight (kg)	Approximately 4.2 kg

Key Features

Practical Function

- Intuitive touch control, covering almost all the major mixing functions.
- The mixer interface can be adjusted for each channel control, including solo, mute, audio-visual, fader, you can see the full level meter.
- Tons of built-in processing. Choice of powerful, touch-sensitive plug-ins, 4-band EQ, gate and compression on inputs, 31-band GEQ and com/limiter on outputs, global reverb and delay.

Flexible Configuration

- Each channel can edit their own name and icon for easy identification, the icon can be imported from a picture library.
- Power and 48V phantom power switches and LEDs round out the mixer.
- Seamless wired to wireless mixing, turn the room from anywhere, get on stage to ring out monitors, personal monitor mixing with access control ability.

Flexible Expansion

- Use up to 10 iOS devices simultaneously.
- Standard Ethernet or Dante™ digital soundcard available, can connect the MIXX12 to any Dante™ device.

Clear Sound Quality

- Ultra low-noise, high-headroom design.

Dante™
SPOKEN HERE



Dante™ upgrade card

Dante-equipped models enable multi-channel audio networking over Ethernet. Standard Ethernet or Dante™ digital networked audio configurations available. Ethernet digital audio of Multi channel, with 24-Bit depth and 48 KHz sample rate. Plug and play networking function, with automatic device discovery function and system configuration. Dante™ upgrade card available for standard Ethernet models. Dante virtual sound card license included to connect a computer to a Dante network for recording, playback and Internet calling between Dante-equipped devices (download Dante virtual sound card at audinate.com)