## MT-PowerAUDIO

### **AM-50**



# Home intelligent music control system

• Operating temperature:-5-60.

• Power supply: AC 20V 50Hz.

• Output power: 25W+25W (MAX)

Output impedance: 8 Ω

• Frequency response: 20Hz-20KHz

• Infrared remote control distance: ≤ 8M

● Bluetooth transmission distance: ≤ 8M

• Dimensions:  $86 \times 86 \times 51$ MM

• Hole size:  $72 \times 72 \times 50$ MM

#### Instructions for use:

Power switch: wave power switch to the left to boot, 3-5 seconds into the boot of the machine interface

M: Bluetooth/music/radio/voice switching Play/pause button: in music play pause, long radio automatically searches for radio stations and in other functions short press ban function Previous track key: in music, a song choice on the radio on channel select

The next song key: next song in the music selection, under radio on channel select VOL keys: volume, with the key combination for curved up and down volume adjustment, short press VOL up and down song combinations you can adjust the volume size, shortpress m key to exit.





### New digital amplifier technology:

low distortion, low noise, high efficiency, goodquality, good sound quality.

High-fidelity stereo sound: the ability to restore "credibility" very high source of sound and acoustic positioning.

Audio format: supporting APE,MP3. WMA music formats.

Bluetooth function: can use a mobile phone with Bluetooth functions such as intelligentelectronic products (such as Iphone,Ipad) for music enjoyment experience (nativepairing password is: 1234)

Audio features: Rock, pop, classic, jazz, bass and many other sound effects to choosefrom.

Choose a variety of play modes: single loop, all loop and other models to choose from.

5-channel audio source select: 1 public source (wiring input) and 4-channel local sound source (FM.TF,USB,BLUETOOTH)

1 public source: General home wiring public computer audio source. DVD audio sources. Built-in radio: built-in digital FM radios, 30 radio store.

External TF card through a card reader to download the update.

#### USB:

Audio output functions: this product being played on any sound source can be output to separate amplifier controller, shared.