

RDA20

DANTE AUDIO NETWORKED
ENABLED SPEAKER SYSTEM

RDA DANTE AUDIO NETWORKED
ENABLED SPEAKER SYSTEM

Dante™
SPOKEN HERE



The RDA20 is an integrated active full frequency speaker with network transmission and pure digital power amplifier. The speaker is powered by PoE+ network switch meaning no external power supply is required. The speaker includes a Class D amplifier which provides. Connect a network cable to communicate with the built-in Dante module to realize network audio signal transmission. By automatically assigning an IP address through the router DHCP, it can transmit signals with Dante's audio matrix in the LAN, and it is easy to set up a full digital network sound reinforcement system. Suitable for education, hospitals, small and medium-sized conference rooms, home theaters, restaurants, houses of worship and other places.

Product Specification



Power supply:	standard POE / POE +
Supply voltage:	37V-57V
Output power:	POE 10W / POE + 20W
Frequency response (-3dB):	85Hz-17KHz
Sound pressure level output (-6dB):	110dB / aes continuous; 113dB / peak
Coverage angle:	horizontal / vertical 90° / 90°
Input jack:	RJ45
Size (mm):	(w) 132 * (d) 160 * (h) 236
Weight:	about 2.93KG
Accessories:	wall bracket

RDA20

Dante Audio Networked
Enabled Speaker System

Key Features

Flexible Expansion

· RJ45 connection for audio from PoE+ Ethernet. Automatically assign an IP address through the router DHCP.

Powerful Function

· With high efficiency and high sound output, excellent sound quality, perfect protection function and good electromagnetic compatibility characteristics.
· Full frequency speaker integrated with network transmission and pure digital power amplifier. router DHCP.