

MA60

Half rack mixing amplifier, 60W @
100 volt



The compact 9.5" MA60 mixing amplifier has an unseen intuitive user friendly interface and ground breaking logical rear panel. The unit comes with 1 mic/line input and 2 stereo line, mono summed inputs.

On the rear you can find smart left-to-right 4 level priority system for audio routing, an emergency input, paging mic with chime and a 24VDC override output. The design of the MA60 is a true redefinition of the mixing amplifier that goes back to the basics. Everyone will understand how to install or operate these units in a blink of an eye.

TECHNICAL SPECIFICATIONS

height- rack units (1U=44 mm) in U	2	depth (build in) in mm	240
depth (incl front) in mm	250	power supply	100 - 240 VAC
power consumption (max) in watts	100	output power RMS 100 volts in watts	60
output power RMS 4 ohms in watts	60	dynamic output power 100 volts in watts	60
minimum impedance load in ohms	4	output power tapings	70 - 100 volts - 4 ohms
zone outputs	1	MIC inputs balanced	2
inputs with Phantom power	1	line input unbalanced	2
tone control	yes	priority switch	2
VOX mute	yes	chime	yes
emergency input	1	priority output	1
priority levels	4	power amp topology	class-D
frequency response (in Hz)	60 - 20 k	cooling system	convection
applicable in 100V	yes	applicable low impedance	yes
Net weight product (kg)	2.6		

MORE PICTURES



ACCESSORIES



MICPAT-D

All call dynamic paging microphone



D-ALINP

Active local input panel Decora style, white



ALINP

Active local input panel